

# Using Server Parameters in Helix ALM RSS Feeds

If your web server is configured to allow access to multiple Helix ALM Servers from a single CGI, you can specify the server to connect to in URLs for RSS feeds. If you do not specify a server, the URL connects to the default server configured on the web server.

## SERVERADDR and SERVERPORT parameters

Add the SERVERADDR and SERVERPORT parameters to connect to a specific Helix ALM Server computer based on the IP address.

For example, the following URL connects to the Wysicorp project on a server hosted on the computer with 123.456.789.101 as the IP address on port 1566:

```
http://localhost/cgi-bin/ttpubdata.exe?command=rss&serveraddr=123.456.789.101&serverport=1566&project=Wysicorp&filterID=28&linktype=http
```

The SERVERADDR and SERVERPORT parameter must both be specified. An error is returned if one of the values is missing.

## SERVERNAME parameter

Add the SERVERNAME parameter to connect to a specific server computer based on the server name configured on the web server. The name is configured using the Helix ALM Registry Utility.

For example, the following URL connects to the Wysicorp project on the 'Development' server:

```
http://localhost/cgi-bin/ttpubdata.exe?command=rss&servername=Development&project=Wysicorp&filterID=28&linktype=http
```

---

Article ID: 464

Last updated: 02 Jun, 2017

Revision: 4

Helix ALM (formerly TestTrack) -> Using Server Parameters in Helix ALM RSS Feeds

<http://www.seapine.com/knowledgebase/index.php?View=entry&EntryID=464>